brother ®



High quality printing

Fast 16ppm print speed

Exceptional value

Brother HL-2030

Stylish and compact 1



Brother HL-2030 Laser printer High quality mono printing from a compact, stylish machine.



Always at your side

www.brother.co.uk u.html ons.brother.co

Brother HL-2030 laser printer

Stylish

Duplex

Contact:

Manual Duplex

The Brother HL-2030 is stylishly designed and compact enough to fit onto a shelf or workstation. It produces printouts with the speed and quality you would expect from a more expensive machine.

Connectivity

Installation is straightforward – simply plug in the power cable, click through the installation CD, and you will be printing minutes later. Compatible with both PC and Apple systems, the HL-2030 uses a USB connection to ensure connectivity with most modern devices.

Ample capacity

The 250 sheet paper tray provides ample capacity and there is also the option of a single sheet manual feed. Thanks to a seperate toner cartridge & drum, you can be confident that this machine offers economical printing.

Stylish & compact designPrint speed of up to 16ppm

HQ1200 (2,400 x 600dpi)

Laser print quality

- Mac[®], Linux & PC compatible
- USB connectivity
- Up to 250 sheet paper tray
- Single sheet manual feed







| Engine | | | |
|---|--|--|--|
| Technology Print Speed First Print Time Resolution | A4 Windows [®] 95 / 98 / Me / NT [®] 4.0 / 2000 / XP Mac OS [®] 9.1-9.2, OS [®] X 10.2.4 or greater Linux | Electrophotographic Up to 16 ppm Less than 10 seconds HQ1200 (2,400 x 600) / 600 / 300dpi 2000 / XP HQ1200 (2,400 x 600) / 600 / 300dpi 600 / 300 dpi | |
| Controller | | | |
| Processor Memory | | SPARClite 96MHz 8MB | |
| Interface | Standard | Full-Speed USB 2.0 | |
| Network Connectivity | Wireless (Optional) Supported Protocol | NC-2200w (USB) 802.11b wireless device TCP/IP ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS, DNS, LPR/LPD, Raw Port/Port9100, SMB Print, IPP, FTP, mDNS,TELNET, SNMP, HTTP | |
| Emulation | | GDI | |
| Software | | | |
| Printer Driver | For Windows® For Macintosh® For Linux (Download from http://solutions.brother.com) Interactive Help | GDI Printer Driver for Windows [®] 98 / Me and 2000 / XP Brother Laser Driver for Mac 9.1-9.2, Mac OS [®] X 10.2.4 or greater GDI Printer Driver for Linux Instructional movie for the solution | |
| ounties | interactive neip | when any error message appears on the Status Monitor. | |
| Control Panel | | | |
| Display | LED | 4 LED (Toner/Drum/Paper/Ready) | |
| Paper Handling | | | |
| Paper Input | Manual Feed Slot Paper Tray | 1 Sheet up to 250 Sheets | |
| Paper Output | | up to 100 Sheets can be stored in the output tray | |

Yes

| Media Types | Manual Feed Slot Paper Tray | Plain Paper, Bond Paper, Recycled Paper, Envelopes, Labels and Transparencies Plain Paper, Bond Paper, Recycled Paper, Transparencies (up to 10 sheets) |
|------------------------|---------------------------------|--|
| Media Weights | Manual Feed Slot | 60 - 161 g/m2 (16 - 43 lb) |
| Media Sizes | Paper Tray Manual Feed Slot | 60 - 105 g/m2 (16 - 28 lb) Width 69.9 to 215.9 mm, Length 116 |
| weula sizes | Manual reed Siot | to 406.4 mm (Width 2.75" to 8.50"", Length 4.57"" to 16"") |
| | Paper Tray | A4, Letter, B5(JIS), B5(ISO), A5, B6, A6, Exe |
| Printer driver fu | inctions | |
| Page Layout | N in 1 Printing | Condense 2, 4, 9, 16 or 25 pages into 1 page |
| | Poster Printing | Enlarge 1 page to print over 4, 9, 16 or 25 pages |
| Others | Quick Print Setup | A printer driver function that enables you to |
| | | change the driver setting without opening Property dialog. |
| | Status Monitor | A function to indicate the printer error on the PC. |
| Supplies | | |
| Toner | TN-2000 | Approx 2,500 A4/LTR pages @ 5% coverage |
| Drum | DR-2000 | Up to 12,000 A4/LTR pages (1 page per job) |
| Dimensions / W | /eights | |
| Dimensions (W x D x H) | | 371 x 361 x 165.5 mm |
| Weights | | 6.5kg |
| Other | | |
| Power Consumption | Printing | Less than 450W |
| | Standby | Less than 70W |
| | Sleep | Less than 5W |
| Noise Level | Sound Pressure / Power Printing | Less than 51 dB(A) / Lwad 6.2B(A) |
| Fastan | Sound Pressure / Power Standby | Less than 30 dB(A) / Lwad 4.3B(A) |
| Ecology | Power Saving Toner Saving | Yes |
| | Ioner Saving | 162 |



brother &



Brother UK Ltd Audenshaw, Manchester M34 5JD

Audenshaw, Manchester M34 5JD Tel:0870 830 4000 (National Rate Call) Fax:0870 830 4031 Web-site: www.brother.co.uk

Your calls to us may be monitored or recorded for training purposes.

Specification correct at time of going to print. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.

UKAS