



High quality printing



Network ready



Fast 20ppm print speed



Outstanding value



Brother HL-2070N Laser printer

A stylish, compact machine producing quality mono prints with full network connectivity as standard.



Always at your side

Brother HL-2070N network ready laser printer

Feature rich

The Brother HL-2070N has been designed with the printing needs of small businesses in mind. It is small enough to free up much needed space on the workstation or desk, yet comes complete with a range of features you would expect to find in larger models.

Network ready

Impressive print quality and speed makes the HL-2070N the ideal choice for your mono printing requirements. The machine is network-ready straight from the box and together with its 16 MB memory and a 250 sheet paper tray, it can easily cope with the demands of multiple users. Thanks to a separate toner cartridge and drum, you can be confident of the cost efficiency of this machine.

Connectivity

To maximise the flexibility of the HL-2070N, it supports most PC and Mac computing environments, and is equipped with parallel and USB ports as standard.

- Stylish & compact design
- USB and parallel connectivity
- Print speed of up to 20ppm
- Network ready
- Laser print quality
- Up to 250 sheet paper tray
- HQ1200 (2,400 x 600dpi)
- Single sheet manual feed
- Mac®, Linux & PC compatible



Engine

Technology	A4	Electrophotographic
Print Speed		Up to 20 ppm
First Print Time		Less than 10 seconds
Resolution	Windows® 95 / 98 / Me and NT® 4.0 / 2000 / XP Mac OS® 9.1-9.2, MacOS® X 10.2.4 or greater Linux	HQ1200 (2400 x 600) / 600 / 300dpi HQ1200 (2,400 x 600) / 600 / 300dpi 600 / 300 dpi

Controller

Processor Memory Interface	Standard	SPARClite 133MHz 16MB Full-Speed USB 2.0, IEEE 1284 Parallel, 10/100 BASE-TX Ethernet
Network Connectivity	Standard	10/100 BaseTX
	Supported Protocol	TCP/IP, ARP, RARP, BOOTP, DHCP, APIPA (Auto IP), WINS/NetBIOS, DNS, LPR/LPD, Raw Port/Port9100, SMB Print, IPP, FTP, mDNS, TELNET, SNMP, HTTP
	Wireless (Optional)	NC-2200w (USB) 802.11b wireless device
	Supported Protocol	TCP/IP, ARP, RARP, BOOTP, DHCP, APIPA (Auto IP), WINS/NetBIOS, DNS, LPR/LPD, Raw Port/Port9100, SMB Print, IPP, FTP, mDNS, TELNET, SNMP, HTTP
	Management Tool	BRAdmin Professional, Web BRAdmin, Web based management
Emulation Resident Fonts	PCL	PCL® 6, IBM® Proprinter XL, Epson® FX-850 PCL: 49 scalable fonts, 12 bitmap fonts, 11 bar codes

Software

Printer Driver	For Windows® For Macintosh® For Linux (Download from http://solutions.brother.com)	PCL Printer Driver for Windows® 95 / 98 / Me / NT® 4.0 / 2000 / XP Brother Laser Driver for Mac® 9.1-9.2, Mac® OS X 10.2.4 or greater GDI Printer Driver for Linux
Utilities	Interactive Help	Instructional movie for the solution when any error message appears on the Status Monitor.

Control Panel

Display	LED	4 LED (Toner/Drum/Paper/Ready)
---------	-----	--------------------------------

Paper Handling

Paper Input	Manual Feed Slot Paper Tray	1 Sheet up to 250 Sheets
Paper Output		up to 100 Sheets can be stored in the output tray
Duplex	Manual Duplex	Yes

Media Specifications

Media Types	Manual Feed Slot Paper Tray	Plain Paper, Bond Paper, Recycled Paper, Envelopes, Labels and Transparencies Plain Paper, Bond Paper, Recycled Paper, Transparencies (up to 10 sheets)
Media Weights	Manual Feed Slot Paper Tray	60 - 161 g/m2 (16 - 43 lb) 60 - 105 g/m2 (16 - 28 lb)
Media Sizes	Manual Feed Slot Paper Tray	Width 69.9 to 215.9 mm, Length 116 to 406.4 mm (Width 2.75" to 8.50", Length 4.57" to 16") A4, Letter, B5(JIS), B5(ISO), A5, B6, A6, Exe

Printer driver functions

Page Layout	N in 1 Printing Poster Printing	Condense 2, 4, 9, 16 or 25 pages into 1 page Enlarge 1 page to print over 4, 9, 16 or 25 pages
Others	Quick Print Setup Status Monitor	A printer driver function that enables you to change the driver setting without opening Property dialog. A function to indicate the printer error on the PC.

Supplies

Toner	TN-2000	Approx 2,500 A4/LTR pages @ 5% coverage
Drum	DR-2000	Up to 12,000 A4/LTR pages (1 page per job)

Dimensions / Weights

Dimensions (W x D x H)	371 x 361 x 165.5 mm
Weight	6.5kg

Other

Power Consumption	Printing Standby Sleep	Less than 450W Less than 70W Less than 7W
Noise Level	Sound Pressure / Power Printing Sound Pressure / Power Standby	Less than 51 dB(A) / Lwad 6.2B(A) Less than 30 dB(A) / Lwad 4.3B(A)
Ecology	Power Saving Toner Saving	Yes Yes



Contact:

At your side.
brother®



Brother UK Ltd
Audenshaw, Manchester M34 5JD
Tel:0870 830 4000 (National Rate Call) Fax:0870 830 4031
Web-site: www.brother.co.uk

Your calls to us may be monitored or recorded for training purposes.
Specification correct at time of going to print. Brother is a registered trademark of Brother Industries Ltd.
Brand product names are registered trademarks or trademarks of their respective companies.